

KX3 80m / 160m BPF & LPF Rework Instructions

The following changes improve IMD3 dynamic range for 80m and 160m receive.

Replace **L3** and **L48** in the T/R high-pass filter with E690308 (Digi-Key 490-5713-1-ND). These are 3.9 uH Murata LQW2UAS3R9J00L SMD inductors.

Replace **L20** and **LC** in the Band-pass filter array with E690307 (Digi-Key PCD1139CT-ND). These are 4.7 uH Panasonic ELJ-NA4R7JF SMD inductors.

