

etc/asterisk/echolink.conf (Sample of my configuration)

```
[el0]
confmode=no
call=MY CALLSIGN -L ; Change this! Registered Callsign -L or -R
pwd=My Password ; Change this! Registered Password
name=My Name ; Change this to your real name!
qth=Location ; Change this to your actual QTH!
email=My Email address ; Change this! Valid Email address
maxstns=20 ; Maximum number of station that can connect to you
rtcptimeout=10
node=00000 ; Change this! Echolink Node Number
recfile=/tmp/recorded.gsm
astnode=XXXXX ; Change this to your active Allstar node number!
context=radio-secure
server1=oceania.echolink.org
server2=server2.echolink.org
server3=server3.echolink.org
naeast.echolink.org
nasouth.echolink.org
;servers.echolink.org
;backup.echolink.org
; Change The following setting to your parameters
;THIS IS FOR THE ECHOLINK STATUS PAGE
freq=145.400 ; Freq in MHz
tone=100.0 ; CTCSS Tone (0 for none)
lat=40.7012345
lon=-73.223457
power=9 ;0=0W, 1=1W, 2=4W, 3=9W, 4=16W, 5=25W, 6=36W, 7=49W,8=64W,9=81W(Power in
Watts)
height=3 ;0=10' ,1=20',2=40',3=80' ,4=160' ,5=320' ,6=640' ,7=1280',8=2560',9=5120' (AMSL in
Feet)
gain=6 ;Gain in db (0-9)
dir=0 ;0=omni,(Direction)
;deny=
;permit=
```