

WriteLog on the air Keyboard Shortcuts V10.09

Log window.....	CTL-N
enter with cursor in Edit mode	CTL-Y
(use arrow keys to move to desired QSO and field)	
Delete QSO	Right-Click QSO
Ignore QSO for scoring.....	highlight QSO & type X
restore:	highlight QSO & type Space
QSL, mark to send.....	Right-Click QSO
QSO, correcting:	double-click field to open QSO Edit
save change	Enter
undo change before saving.....	CTL-Z
window close	double-click on background
Scroll: down one line.....	CTL-↓
down one page	Page Down
up one line	CTL-↑
up one page	Page Up

Messages	End all messages with a space.
Function keys: program with "Setup CW/RTTY Messages"	
pull-down menu or Shift-Fn (voice).	
Unshifted F key	Shift-F (CW only)
F1*	CQ*
F2	Exchange
F3	TU QRZ
F4	My call
F5	His call
F6	QRL?
F7	QRL!
F8	?
F9	QTC rcv: QSL!
F10	his call, Exchng or QSO B4
F11	QTC rcv: QRV!
	QTC xmit: QSL?
	QTC xmit: QRV?

Repeat field in exchange..... Click button over field
 To program:Shift-Click button over field

Special message parameters:	
CW speed up / down	< or >
CW prosigns:	AA + BT - AR @ KN # AS] SK [error Delete
Field <i>n</i> from QSO Entry window.....	%Fn
Hello name (extract from "Hi" file).	%H
His call	%D or
If cursor in call field, wait until user finishes typing call before continuing.....	%C
Insert data from user (prompt now).....	%I
Memory <i>n</i> inserted here (1-11, 21-31=shift)	%Mnn
My number.....	%n, n=1 to 5 (min # digits)
Previous QSO's exchange field <i>n</i>	%Pn
QSO before message.....	%B text %B
RTTY Return key	%R
RTTY end of transmission.....	%E
Speed increase or decrease.....	< or >
Time of day	%T

Rate window: Select single- or all-band rate ...Right-click

RTTY window	Right-click for other actions
Callsigns, queue of RTTY received.....	ALT-C
Letters case, shift receive to	ALT-L
Move selected characters to QSO Entry window	
Left click	
Invert Ltrs/Figs.....	Shift-Left click
Only highlighted part of call.....	CTL-Left click

QSO Entry window.....	CTL-P
Abort message in progress.....	Escape or Shift-Home or CTL-C*
Band: next lower freq	ALT-F1
next higher freq	ALT-F2
Callsigns, queue of RTTY received	ALT-C
CQ message	F11 or F1* or Enter (cursor in empty callsign field)
Cursor, move to	
end of current field.....	End
end of last field.....	CTL-E ("end")
left one character.....	← or CTL-B ("backward")
next field.....	Space or Tab
previous field.....	Shift-Tab
right one character.....	→ or CTL-F ("forward")
start of current field.....	Home
start of first (leftmost) field.....	CTL-A
CW: speed: faster.....	ALT-F10 or Page-Up
slower.....	ALT-F9 or Page-Down
weight: heavier.....	Shift-PgUp
lighter	Shift-PgDn
Delete character	
previous character.....	Backspace
under cursor.....	CLT-D or Delete
Delete in the current field	
entire field.....	CTL-W ("wipe")
to right of cursor.....	CTL-K ("kill")
Delete QSO	ALT-W ("wipe") or CTL-Backspace or F11*
Delete QSO number:.....	Clear the callsign field, or CTL-A & Backspace
Enter QSO:	
Send TU msg (with corrected call if changed)	
+ or Enter (cursor not in callsign field)	
Silent logging	Shift-Enter or CTL-Enter
Frequency: go to.....	type freq in call field, Enter
Split transmit freq.....	-
Frequency scratchpad memory	
toggle to/from.....	CTL-Tab
exchange memory with current QSO.....	Shift-click
move between entries.....	Tab, Shift-Tab
set # of scratchpad entries	Right-click
Gab, send a network.....	ALT-G
Go to QSO	enter call fragment (*, ? wildcards) or enter log sequence number then.....
	CTL-G ("go")
Headphone, latch to non-xmtg radio.....	CTL-X**
His Call + Exchange / QSO B4.....	F10 or Insert or Enter (cursor in non-empty callsign field)
Keyboard sending.....	Alt-K
Mode, changing	CTL-F1 or CTL-F2
Note, create a.....	ALT-N
QTC:	
receive QTC window	ALT-R
request fill on QTC # <i>n</i>	ALT-n
send QTC window.....	ALT-S
Radio, switching:	
activate radio with keybd focus for xmit	CTL-R
keybd entry only	Shift-↑ or Shift-↓
keybd entry and transmit	↑ or ↓
transmit only	CTL-↑ or CTL-↓
Received calls (RTTY only)	ALT-C
Repeating CQs.....	ALT-T ("timed repeat")
RIT, clear the offset.....	*
RTTY receive: shift to Letters case.....	ALT-L
Spot: announce.....	CTL-T or ALT-F3
Return to 0.00 kHz	F12

* if CtCompatibleAccel=YES

** with W5XD outboard keyer