

Anti-Chuff Modification

Sangean ATS-808 / Realistic DX-380 / Siemens RK661

This document generated by Dave Zantow N9EWO

This requires removing TINY 2 SURFACE MOUNT resistors from the main board (R109 and R110, both 12K value). No need to remove the main board as the resistors are located on the backside on the right side of the main board near the bottom (as viewed with rear cover removed). This modification will allow microprocessor noises / band changes etc...to irk through. But is much improved than having the very annoying muting when tuning. The changeling part is to reassemble the set with all of the switches on either side (have to be sure ALL the slide switches line back up with the switch levers).

IMPORTANT: Modification is *ONLY* for those who have soldering experience with TINY surface mounted parts.

WARNING : MODIFICATION DONE AT YOUR OWN RISK !

