

Sherwood Engineering HF Test Results

Model CommRadio CTX-10

Serial # 0155

Test Date: 11/24/2020

Dynamic Range of radio, no preamp

| | | |
|----------------------|----|----|
| Dynamic Range 20 kHz | 50 | dB |
| Dynamic Range 10 kHz | | dB |
| Dynamic Range 5 kHz | 45 | dB |
| Dynamic Range 2 kHz | | dB |

| | | |
|---|----|----|
| Blocking above noise floor, 1uV signal @ 100 kHz, AGC On, See notes below on blocking. | 49 | dB |
|---|----|----|

| | | |
|--|--|-----|
| Phase noise (normalized) at 2.5 kHz spacing: | | dBc |
| Phase noise (normalized) at 5 kHz spacing: | | dBc |
| Phase noise (normalized) at 10 kHz spacing: | | dBc |
| Phase noise (normalized) at 20 kHz spacing: | | dBc |
| Phase noise (normalized) at 30 kHz spacing: | | dBc |
| Phase noise (normalized) at 40 kHz spacing: | | dBc |
| Phase noise (normalized) at 50 kHz spacing: | | dBc |
| Phase noise (normalized) at 80 kHz spacing: | | dBc |
| Phase noise (normalized) at 100 kHz spacing: | | dBc |
| Phase noise (normalized) at 200 kHz spacing: | | dBc |
| Phase noise (normalized) at 300 kHz spacing: | | dBc |
| Phase noise (normalized) at 400 kHz spacing: | | dBc |
| Phase noise (normalized) at 500 kHz spacing: | | dBc |

| | | |
|--|------|-----|
| Noise floor, SSB bandwidth 14 MHz, no preamp | -110 | dBm |
| Noise floor, SSB bandwidth 14 MHz, Preamp 1 On | -120 | dBm |

| | | |
|--|---|----|
| Sensitivity SSB at 14 MHz, no preamp | 5 | uV |
| Sensitivity SSB at 14 MHz, Preamp 1 On | 1 | uV |

| | | |
|--|------|-----|
| Noise floor, 500 Hz, 14.2 MHz, no preamp | -120 | dBm |
| Noise floor, 500 Hz, 14.2 MHz, Preamp 1 On | -134 | dBm |

| | | |
|-----------------------------|----|----|
| Gain of preamp(s) Preamp | 20 | dB |
|-----------------------------|----|----|

| | | |
|------------------------------------|-----|----|
| AGC threshold at 3 dB, no preamp | 5.5 | uV |
| AGC threshold at 3 dB, Preamp 1 On | 0.7 | uV |

Notes:

The lowest blocking and the lowest dynamic range I have ever measured.

Dynamic range values are actually the point where blocking begins.

With the preamp ON, there are lots of spurious noises and birdies.

There was no practical reason to try to measure LO phase noise since blocking dominates the entire operation of the radio.

Sensitivity measurements are approximate since the radio does not quiet 10 dB with a strong signal, only about 8 dB.

Preamp gain is estimated at approximately 20 dB.