



Uniden Bearcat BC-796D (Trunktracker IV)



(C) 2000-2010
by SMOOFV

Last modified 2005-10-09

| | |
|----------------------------|--|
| Type: | HF/VHF/UHF receiver/scanner |
| Frequency range: | 25-512 / 806-956 / 1240-1300 MHz Cellular blocked |
| Mode: | AM/FM/WFM/APCO25 Digital |
| Sensitivity: | N/A |
| Selectivity: | N/A |
| Image rejection: | N/A |
| Voltage: | 13.8 VDC |
| Current drain: | Max ? mA |
| Impedance: | 50 ohms, BNC |
| Dimensions (W*H*D): | 177*61*167 mm |
| Weight: | 1.44 Kg |
| Manufactured: | 2004-200x |
| Other: | 1000 memories in 10 banks. CTCSS/DCS. Tracks Motorola I, II & III and EDACS and LTR |
| Related documents: | User manual (1.2 MB) |