

Ombouw project LAP 76k8+ PI8HGL

Ombouw DDS modem naar 76K8 / 153K6

Te wijzigen onderdelen:

| PART | | 9K6 | 76800 | 153600 |
|------|-----|--------|-------|--------|
| DCD | R49 | 100K | 15K | 8K2 |
| DCD | R34 | 47K | 47K | 39K |
| RX | R10 | 100K | 15K | 8K2 |
| RX | R11 | 82K | 12K | 4K7 |
| RX | R12 | 39K | 5K6 | 2K7 |
| RX | R13 | 27K | 3K9 | 1K8 |
| TX | R40 | 100K | 15K | 8K2 |
| TX | R41 | 56K | 8K2 | 5K6 |
| RXC | C13 | 4n7 | 680p | 330p |
| RXC | C12 | 100p | 12p | 6p8 |
| RX | C9 | stryof | 220p | 100p |
| RX | C10 | stryof | 1n | 470p |
| RX | C28 | stryof | 1n | 470p |
| TX | C22 | stryof | 3n3 | 470p |
| TX | C24 | stryof | 100p | 47p |
| TX | C25 | stryof | 470p | 220p |
| TX | C26 | stryof | 1n | 150p |

