

CB - TONE - NOR (Normais 1 ~ 40)			CB - HI - NOR (Positivos 60 ~ 104)			CB - LOW - NOR (Negativos -64 ~ -20)		
DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA
1	1	26.965	1	60	27.605	1	-64	26.325
2	2	26.975	2	61	27.615	2	-63	26.335
3	3	26.985	3	62	27.625	3	-62	26.345
31	3 TC	26.995	31	63	27.635	31	-61	26.355
4	4	27.005	4	64	27.645	4	-60	26.365
5	5	27.015	5	65	27.655	5	-59	26.375
6	6	27.025	6	66	27.665	6	-58	26.385
7	7	27.035	7	67	27.675	7	-57	26.395
36	7 TC	27.045	36	68	27.685	36	-56	26.405
8	8	27.055	8	69	27.695	8	-55	26.415
9	9	27.065	9	70	27.705	9	-54	26.425
10	10	27.075	10	71	27.715	10	-53	26.435
11	11	27.085	11	72	27.725	11	-52	26.445
8	11 TC	27.095	8	73	27.735	8	-51	26.455
12	12	27.105	12	74	27.745	12	-50	26.465
13	13	27.115	13	75	27.755	13	-49	26.475
14	14	27.125	14	76	27.765	14	-48	26.485
15	15	27.135	15	77	27.775	15	-47	26.495
15	15 TC	27.145	15	78	27.785	15	-46	26.505
16	16	27.155	16	79	27.795	16	-45	26.515
17	17	27.165	17	80	27.805	17	-44	26.525
18	18	27.175	18	81	27.815	18	-43	26.535
19	19	27.185	19	82	27.825	19	-42	26.545
16	19 TC	27.195	16	83	27.835	16	-41	26.555
20	20	27.205	20	84	27.845	20	-40	26.565
21	21	27.215	21	85	27.855	21	-39	26.575
22	22	27.225	22	86	27.865	22	-38	26.585
23	23	27.235	23	87	27.875	23	-37	26.595
24	24	27.245	24	88	27.885	24	-36	26.605
25	25	27.255	25	89	27.895	25	-35	26.615
26	26	27.265	26	90	27.905	26	-34	26.625
27	27	27.275	27	91	27.915	27	-33	26.635
28	28	27.285	28	92	27.925	28	-32	26.645
29	29	27.295	29	93	27.935	29	-31	26.655
30	30	27.305	30	94	27.945	30	-30	26.665
31	31	27.315	31	95	27.955	31	-29	26.675
32	32	27.325	32	96	27.965	32	-28	26.685
33	33	27.335	33	97	27.975	33	-27	26.695
34	34	27.345	34	98	27.985	34	-26	26.705
35	35	27.355	35	99	27.995	35	-25	26.715
36	36	27.365	36	100	28.005	36	-24	26.725
37	37	27.375	37	101	28.015	37	-23	26.735
38	38	27.385	38	102	28.025	38	-22	26.745
39	39	27.395	39	103	28.035	39	-21	26.755
40	40	27.405	40	104	28.045	40	-20	26.765

CB - TONE - DIM (Positivos 41 ~ 44)			CB - HI - DIM (Positivos 105 ~ 108)			CB - LOW - DIM (Negativos -19 ~ -16)		
DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA
37	41	27.415	37	105	28.055	37	-19	26.775
38	42	27.425	38	106	28.065	38	-18	26.785
39	43	27.435	39	107	28.075	39	-17	26.795
40	44	27.445	40	108	28.085	40	-16	26.805

PA - HI - NOR (Positivos 45 ~ 59)			PA - LOW - NOR (Negativos -79 ~ -65)			PA - TONE - NOR (Negativos -1 ~ -15)		
DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA
15	45	27.455	15	-79	26.175	15	-15	26.815
15	46	27.465	15	-78	26.185	15	-14	26.825
16	47	27.475	16	-77	26.195	16	-13	26.835
17	48	27.485	17	-76	26.205	17	-12	26.845
18	49	27.495	18	-75	26.215	18	-11	26.855
19	50	27.505	19	-74	26.225	19	-10	26.865
16	51	27.515	16	-73	26.235	16	-9	26.875
20	52	27.525	20	-72	26.245	20	-8	26.885
21	53	27.535	21	-71	26.255	21	-7	26.895
22	54	27.545	22	-70	26.265	22	-6	26.905
23	57	27.575	23	-67	26.295	23	-3	26.935
24	55	27.555	24	-69	26.275	24	-5	26.915
25	56	27.565	25	-68	26.285	25	-4	26.925
26	58	27.585	26	-66	26.305	26	-2	26.945
27	59	27.595	27	-65	26.315	27	-1	26.955

Tabela Cobra 148 GTL (PTT frontal) -79 +108 * PLL MMB 8719 * Cristal: 11.112,5 MHZ

Tabela capturada na página www.antoniodomeier.com - Antônio do Méier _AM - RJ - BRASIL Tel: (21)25940777 - (21)982326136