

Gebevorlage G-QSO

CW-Kurs 2001

Michael, DF2OK

Freie Frequenz suchen und dann: QRL? (6-10 Sek. Pause) QRL?

cq cq cq de MYCALL MYCALL MYCALL pse k

CALL de MYCALL = gm | gd | ga dr op es tn timer call =

ur rst ??? ??? = qth | MYQTH MYQTH | nr nr hamburg (2x) (hannover 2x) =

name MYNAME MYNAME = hw? = CALL de MYCALL kn

CALL de MYCALL = ok | rr | <ve> | tn timer rpt es info dr (yl) om ??? =

rig kenwood | knwd | ts820 | wid pwr ??? watts into ant

g5rv | dipol | gpa | 3 el yagi | ??? =

CALL de MYCALL kn

de MYCALL =

ok | rr | <ve> | fb cpi (Nur, wenn es stimmt!) | dr (yl) om ??? =

wx sunny | (nachts) clear | cloudy | overcast (ovc) | humid | rain |

hail | snow | windy | storm(y) = temp (abt) ??c =

CALL de MYCALL kn

de MYCALL =

my key is junker = | these are my first steps in cw = hpe ok ? =

fer ?? yrs i was qrv only on vhf, nw since june on all bands wid new call =

CALL de MYCALL kn

de MYCALL =

ok | rr | <ve> | ok dr om (yl) ??? = nw qru =

tnx fr info | es qso | = mni | tn timer fer | nice | qso =

mni tks fer | nice | qso dr om | dr yl ??? =

qsl(1) sure via darc | buero | direct | es pse qsl = all the best =

vy 73 | 72 (unter QRPern oder an QRPer) | 88 | es best dx = hpe cuagn =

tnx fer nice | fb | qso es hpe cuagn =

gl | mni tks fer | nice | qso es cuagn | cul =

mni tn timer fr my 1st pfx | dxcc | on this band | in cw | =

CALL de MYCALL 73 <sk>

Weitere höfliche Anhängsel an ein QSO-Ende:

gm | ga | gn | ciao (i) | au revoir (f) | cheerio (i) | hasta la vista (ea) |
hei hei (oh) | hej hej (sm) | dsw (ua) | mri xmas | hppy ny | hny