

CB - LOW - NOR ( Normais 1 ~ 40 )			CB - NOR - NOR ( Positivos 60 ~ 104 )			CB - HI - NOR ( Positivos 124 ~ 168 )		
DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA
1	1	26.965	1	60	27.605	1	124	28.245
2	2	26.975	2	61	27.615	2	125	28.255
3	3	26.985	3	62	27.625	3	126	28.265
31	3 TC	26.995	31	63	27.635	31	127	28.275
4	4	27.005	4	64	27.645	4	128	28.285
5	5	27.015	5	65	27.655	5	129	28.295
6	6	27.025	6	66	27.665	6	130	28.305
7	7	27.035	7	67	27.675	7	131	28.315
36	7 TC	27.045	36	68	27.685	36	132	28.325
8	8	27.055	8	69	27.695	8	133	28.335
9	9	27.065	9	70	27.705	9	134	28.345
10	10	27.075	10	71	27.715	10	135	28.355
11	11	27.085	11	72	27.725	11	136	28.365
8	11 TC	27.095	8	73	27.735	8	137	28.375
12	12	27.105	12	74	27.745	12	138	28.385
13	13	27.115	13	75	27.755	13	139	28.395
14	14	27.125	14	76	27.765	14	140	28.405
15	15	27.135	15	77	27.775	15	141	28.415
15	15 TC	27.145	15	78	27.785	15	142	28.425
16	16	27.155	16	79	27.795	16	143	28.435
17	17	27.165	17	80	27.805	17	144	28.445
18	18	27.175	18	81	27.815	18	145	28.455
19	19	27.185	19	82	27.825	19	146	28.465
16	19 TC	27.195	16	83	27.835	16	147	28.475
20	20	27.205	20	84	27.845	20	148	28.485
21	21	27.215	21	85	27.855	21	149	28.495
22	22	27.225	22	86	27.865	22	150	28.505
23	23	27.235	23	89	27.895	23	153	28.535
24	24	27.235	24	87	27.875	24	151	28.515
25	25	27.245	25	88	27.885	25	152	28.525
26	26	27.265	26	90	27.905	26	154	28.545
27	27	27.275	27	91	27.915	27	155	28.555
28	28	27.285	28	92	27.925	28	156	28.565
29	29	27.295	29	93	27.935	29	157	28.575
30	30	27.305	30	94	27.945	30	158	28.585
31	31	27.315	31	95	27.955	31	159	28.595
32	32	27.325	32	96	27.965	32	160	28.605
33	33	27.335	33	97	27.975	33	161	28.615
34	34	27.345	34	98	27.985	34	162	28.625
35	35	27.355	35	99	27.995	35	163	28.635
36	36	27.365	36	100	28.005	36	164	28.645
37	37	27.375	37	101	28.015	37	165	28.655
38	38	27.385	38	102	28.025	38	166	28.665
39	39	27.395	39	103	28.035	39	167	28.675
40	40	27.405	40	104	28.045	40	168	28.685
CB - LOW - DIM ( Positivos 41 ~ 44 )			CB - NOR - DIM ( Positivos 105 ~ 108 )			CB - HI - DIM ( Positivos 169 ~ 172 )		
DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA
37	41	27.415	37	105	28.055	37	169	28.695
38	42	27.425	38	106	28.065	38	170	28.705
39	43	27.435	39	107	28.075	39	171	28.715
40	44	27.445	40	108	28.085	40	172	28.725
PA - NOR - NOR ( Positivos 45 ~ 59 )			PA - HI - NOR ( Positivos 109 ~ 123 )			PA - LOW - NOR ( Negativos -1 ~ -15 )		
DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA	DÍGITO	CANAL	FREQUENCIA
15	45	27.455	15	109	28.095	15	-15	26.815
15	46	27.465	15	110	28.105	15	-14	26.825
16	47	27.475	16	111	28.115	16	-13	26.835
17	48	27.485	17	112	28.125	17	-12	26.845
18	49	27.495	18	113	28.135	18	-11	26.855
19	50	27.505	19	114	28.145	19	-10	26.865
16	51	27.515	16	115	28.155	16	-9	26.875
20	52	27.525	20	116	28.165	20	-8	26.885
21	53	27.535	21	117	28.175	21	-7	26.895
22	54	27.545	22	118	28.185	22	-6	26.905
23	57	27.575	23	121	28.215	23	-3	26.935
24	55	27.555	24	119	28.195	24	-5	26.915
25	56	27.565	25	120	28.205	25	-4	26.925
26	58	27.585	26	122	28.225	26	-2	26.945
27	59	27.595	27	123	28.235	27	-1	26.955

Tabela Cobra 148 GTL (PTT frontal) -15 +172 \* PLL MMB 8719 \* Cristal: 11.325 MHZ

Tabela capturada na página [www.antoniodomeier.com](http://www.antoniodomeier.com) - Antônio do Méier \_AM - RJ - BRASIL Tel: (21)25940777 - (21)982326136